



WARNING:
CAPACITOR ENCLOSURE
DO NOT OPEN WITHOUT
DISCONNECTING FROM POWER
BEFORE HANDLING

5 MINUTE WARNING
LABEL, SUPPLIED LOOSE,
TO BE PLACED ON
CAPACITOR ENCLOSURE

CAUTION:
REWORKING SHOTS REQUIRE SPECIAL
ATTENTION

WARNING:
INTERNAL RESISTANCE DRIVE SYSTEM
REWORKING SHOTS REQUIRE SPECIAL
ATTENTION. REWORKING SHOTS
REQUIRE SPECIAL ATTENTION.
AVERTISSEMENT:
Système à entraînement interne
à rétroaction par courant. Les
opérations de réparation
nécessitent une attention
particulière.

| kVar | Amps | D* | H | A |
|------|------|-----|-----|-----|
| 25 | 3.5 | 110 | 200 | 150 |
| 50 | 7.0 | 110 | 250 | 150 |
| 75 | 10.0 | 110 | 280 | 150 |
| 100 | 14.0 | 110 | 330 | 150 |
| 125 | 17.0 | 110 | 320 | 150 |
| 150 | 21.0 | 110 | 350 | 150 |
| 175 | 24.0 | 135 | 350 | 150 |
| 200 | 28.0 | 135 | 410 | 150 |
| 225 | 31.2 | 175 | 330 | 150 |
| 250 | 34.7 | 175 | 380 | 150 |
| 275 | 38.2 | 175 | 400 | 150 |
| 300 | 41.6 | 175 | 430 | 150 |
| 325 | 45.1 | 175 | 450 | 150 |
| 350 | 48.5 | 175 | 490 | 150 |
| 375 | 52.0 | 175 | 510 | 150 |
| 400 | 55.5 | 175 | 540 | 150 |
| 425 | 58.9 | 175 | 560 | 150 |
| 450 | 62.4 | 175 | 590 | 150 |
| 475 | 65.9 | 175 | 630 | 246 |
| 500 | 69.4 | 175 | 650 | 246 |

* CASE MAY BULGE UP TO 12.7mm.

- Notes:
1. 60kVBL.
 2. 3 Phase.
 3. Internal discharge resistors.
 4. All dimensions in mm.

This drawing is the property of Electrotek Ltd.
The information and technology herein may not
be used nor reproduced without the written
permission of Electrotek Ltd.
All reproductions, in whole or in part, including
shop drawings, shall refer to this clause.

Revised: 08/04/05

Title: 4160 Volt
Medium Voltage
Capacitor

Model: R1000

ELECTROTEK LTD

10116 34 AV SE Calgary, AB
T2G 1V4 Canada
Tel: 403 287 2200 Fax: 403 287 3808
contact@electrotekltd.com
www.electrotekltd.com