



WARNING:
CAPACITOR ENERGY
WARNING: OPENING
OR SHORTING THEN SHORT
BEFORE HANDLING

AVERTISSEMENT:
CHARGES DE CONDENSATEUR
DANGERS DE BRULURE
AVANT DE MANIPULER.

5 MINUTE WARNING
LABEL, SUPPLIED LOOSE,
TO BE PLACED ON
CAPACITOR ENCLOSURE

CAUTION
RECONNECT SPERRY TO CIRCUIT
BEFORE REMOVING THE CAPACITOR
AVANT DE RECONNECTER LE CONDENSATEUR

WARNING:
INTERNAL RESISTANCE MUST BE
DISCONNECTED FROM SUPPLY
BEFORE REMOVING THE PARTS.
AVERTISSEMENT:
NE PAS ENLÉVER DE
PIÈCES SANS DÉCONNECTER
D'ABORD LES RÉSISTANCES
INTERIEURES DES BRANCHES

1/2-13NC X 3/4"
DEEP HOLE

kVAR	Amps	Fuse	D*	H	A
25	3.5	25A	110	200	150
50	7.0	25A	110	250	150
75	10.0	25A	110	280	150
100	14.0	25A	110	330	150
125	17.0	50A	110	320	150
150	21.0	50A	110	350	150
175	24.0	50A	135	350	150
200	28.0	50A	135	410	150
225	31.2	75A	175	330	150
250	34.7	75A	175	380	150
275	38.2	75A	175	400	150
300	41.6	75A	175	430	150
325	45.1	100A	175	450	150
350	48.5	100A	175	490	150
375	52.0	100A	175	510	150
400	55.5	100A	175	540	150
425	58.9	125A	175	560	150
450	62.4	125A	175	590	150
475	65.9	160A	175	630	246
500	69.4	160A	175	650	246

* CASE MAY BULGE UP TO 12.7mm.

- Notes:
1. 60KVBL.
 2. 3 Phase.
 3. Internal discharge resistors.
 4. Three HRC fuses supplied.
 5. All dimensions in mm.

This drawing is the property of Electrotek Ltd.
The information and technology herein may not
be used nor reproduced without the written
permission of Electrotek Ltd.
All reproductions, in whole or in part, including
shop drawings, shall refer to this clause.

Revised: 08/04/05

Title: 4160 Volt Fused
Medium Voltage
Capacitor

Model: R1000F



10116 34 AV SE Calgary, AB
T2G 1V4 Canada
Tel: 403 287 2200 Fax: 403 287 3808
contact@electrotekltd.com
www.electrotekltd.com